

EDS / EFS Series Control Stations

FlexStation™ Control Station Components


Cl. I, Div. 1 & 2, Groups B (Div. 2 only) C, D
Cl. II, Div. 1 & 2, Groups E, F, G
Cl. III
Zone 1 & 2 Group IIB
NEMA 3R, 7B* (Div. 2) CD, 9 EFG, 12

4C

4C

STEP 1 – Select Operator

Pushbutton – front operated, standard black button



Description

Single button for 1 contact block
Single button for 2 contact blocks
Double buttons for 2 contact blocks

Cat.

DEV11
DEV12
DEV22

Options

Specify color for each pushbutton button (ex: DEV11G, DEV22GR). Color is black if unspecified.

Green button - unmarked

Red button - unmarked

Momentary red mushroom head style (not available with lockout or with DEV22)

Lockout with bar and chain (available on DEV11 and DEV12)

Maintained red mushroom head style (lockout comes standard, do not specify S153; not available on DEV22)

Suffix

G

R

S111

S153

S769

Pilot Light – factory sealed, incandescent lamp



Description

Pilot light with red jewel

Pilot light with green jewel

Pilot light with amber jewel

Pilot light with clear jewel

Pilot light with blue LED and clear jewel

Cat.

DEV30 J1

DEV30 J3

DEV30 J6

DEV30 J10

DEV30 J11 LED

Options

LED lamps (standard clear jewel with colored lamp)

24 V lamp (not available with transformer feature)

240 / 120 V pilot light transformer

480 / 120 V pilot light transformer

600 / 120 V pilot light transformer

Suffix

LED

S300

T2

T4

T5

Selector Switch – with standard lockout



Description

2-position (pos. 1 – N.O., pos. 2 – N.C.) for use with 1 or 2 contact blocks

3-position (pos. 1 – N.O., pos. 2 – Open, pos. 3 – N.C.) for use with 1 or 2 contact blocks

3-position (pos. 1 – N.C., pos. 2 – N.O., pos. 3 – N.O. for Switch A)

(pos. 1 – N.O., pos. 2 – N.O., pos. 3 – N.C. for Switch B) for use with 2 contact blocks

Cat.

DEV42

DEV43

DEV44

Options

Spring return to center from right (For DEV43 or DEV44 only)

Spring return to center from left (For DEV43 or DEV44 only)

Spring return to center from right and left (For DEV43 or DEV44 only)

Key Operated – removable from all positions

Key Operated – removable from left position for DEV42 or from center for DEV43 and DEV44

Key Operated – removable from right position for DEV42 or from left for DEV43 and DEV44

Key Operated – removable from right position for DEV43 and DEV44

Suffix

S634

S635

S842

S847 K1

S847 K2

S847 K3

S847 K4

STEP 2 – Select Contact Block (if required). For product details see page 565.

Contact Block



Description

Contact block, 1 NO and 1 NC, 10A, 600VAC, A600 rating

Cat.

ESWP126

For additional technical information see page 565.

Note - Each control station will accept a maximum of three contact blocks. Select device operators accordingly. DEV12, DEV22 and DEV44 may not be used on a three-operator (DS443-SA) cover. DEV42 and DEV43 may not be used on a three-operator cover when using them with two contact blocks.