E2C34G1, Substation - Copper Tap Adapter



By Burndy
Catalog # E2C34G1

Multi-tap, range-taking cast copper alloy connector designed to take 2 conductors from a single secondary transformer outlet.

Features

- Copper Transformer Tap Adapter
- Tension Rating: ANSI C119.4 Class 3 (Non Tension)
- Multi-tap, range-taking cast copper alloy connector designed to take 2 conductors from a single secondary transformer outlet

Application

Substation

General

Catalog Number	E2C34G1
EU RoHS Indicator	Yes
Installation Torque Recommended in-lb	480 LBS/in
Material	Copper Alloy
Sub Brand	MECHANICAL CONNECTOR
Type	Adapters
UPC	781810002063
UPC 14 Digit GTIN	00781810002063

Dimensions

Dimension - D inch	3.75 in
Dimension - Height fraction	3-7/8
Dimension - Height inch	3.88 in
Dimension - Height mm	98.6 mm
Dimension - Pin Diameter inch	0.78 in
Dimension - Width fraction	3-1/2 in
Dimension - Width inch	3.50 in
Dimension - Width mm	89 mm

Conductor Related

Conductor - Copper Solid Size	1/0 AWG;2/0 AWG;3/0 AWG;4/0 AWG
Conductor - Copper Solid Size Range	1/0 AWG-4/0 AWG
Conductor - Copper Str Size Range	1/0 -500 kcmil
Conductor Type	• CU C Str-Size • CU C Solid-Size
Number of Conductors	2

Certifications And Compliance

Buy America(n) Qualified	Contact Manufacturer
Standards - RoHS Compliance Status	EX
UL Listed	No

Logistics

Carton Quantity	3
Minimum Pack Quantity	1

Product Assets

3D Models - E2C34G1_MODEL-PDF
3D Models - E2C34G1_MODEL-STEP
3D Models - E2C34G1_MODEL-IGES
Catalogs - BURNDY Master Catalog - Section H - Overhead Distribution
Catalogs - BURNDY Master Catalog - Full Line BURNDY Catalog
Catalogs - BURNDY Master Catalog - Section L - Bolted Substation
Customer Notices - Prop 65 Notice
Interactive Catalog - BURNDY Full-Line Digital Catalog
Product Cross Section Image(s) - BUR_ECG_LineArt
Sales Drawings - sc042041-01
Specifications - E2C34G1

©2025 Hubbell Incorporated. All rights reserved