GE Lighting

82143 - Q50GU10FL/RVL-CD

GE reveal® halogen 50 watt MR16 1-pack


• GE reveal® halogen bulbs fill rooms with clean, beautiful light®. GE reveal® technology filters out dull, yellow rays, bringing out colors and patterns that go unnoticed under regular incandescent light. Use color-enhanced full-spectrum GE reveal® halogen GU10 bulbs to make colors and patterns pop in indoor track and recessed fixtures.

• Lasts 2.7 years based on 3 hours per day usage

• Estimated yearly energy costs $6.02 based on 3 hours per day $0.11 per kWh

• MR16 shape with GU10 base for use directional fixtures such as recessed can lighting









GENERAL CHARACTERISTICS

Lamp Type	Halogen - MR
Bulb	MR16
Base	GU10
Filament	CC-2V
Rated Life (NOM)	3000.0 h
Primary Application	Indoor Floodlight

PHOTOMETRIC CHARACTERISTICS

Initial Lumens (NOM)	400.0
Center Beam Candlepower (CBCP) (NOM)	400.0
Color Temperature (NOM)	2750.0 K

ELECTRICAL CHARACTERISTICS

Wattage (NOM)	50.0
Voltage (NOM)	120.0

DIMENSIONS

Maximum Overall Length (MOL) (NOM)	2.125 in(54.0 mm)
Bulb Diameter (DIA) (NOM)	2.000 in(50.8 mm)

PRODUCT INFORMATION

Product Code	82143
Description	Q50GU10FL/RVL-CD
Standard Package	Case
Standard Package GTIN	10043168821435
Standard Package Quantity	6
Sales Unit	Unit
No Of Items Per Sales Unit	1
No Of Items Per Standard Package	6
UPC	043168821438

CAUTIONS & WARNINGS

Caution

• Lamp may shatter and cause injury if broken
  - Dispose of lamp in a closed container.
  - Do not use lamp if outer glass is scratched or broken.

Warning

• Risk of Electric Shock
  - Turn power off before inspection, installation or removal.
• Risk of Fire
  - In table lamp, use only with shade.
  - Keep combustible materials away from lamp.
  - Use in fixture rated for this product.
• Pressurized lamp--unexpected rupture may cause injury, fire, or property damage
  - Do not exceed rated voltage.
  - Do not use lamp if outer glass is scratched or broken.
• A damaged lamp emits UV radiation which may cause eye/skin injury
  - Turn power off if glass bulb is broken. Remove and dispose of lamp.
• Risk of Burn
  - Allow lamp to cool before handling.